

FLM

Mini Flood Lights




Pictured: FLM-50W-3CCT-LV

CSC LED's FLM Mini Flood Lights are ideal for landscaping, patios, security lighting, signs, and building facades. Excellent replacement for quartz halogen fixtures.

- Colour Selectable (3000K / 4000K / 5000K) *30W-90W models*
- Die-cast aluminum housing with cooling fins for superior heat dissipation
- High-impact polycarbonate lens/optics
- Rugged polyester powder coat finish (bronze)
- Built-in photocell
- 0.5m power cord



*Excludes:
FLM-15W-40K-LV-YK,
FLM-15W-40K-LV-KN



Power Selectable (70%-100%)
30W-90W models



Wattage
15W-90W



Lumens
1,603 lm - 11,320 lm



Voltage
120-277V,
120-347V



CCT
4000K,
3000K / 4000K / 5000K

FLM Mini Flood Lights

PRODUCT #	WATTS	VOLTAGE	CCT	LUMENS*	EFFICACY*	DLC
FLM-15W-40K-LV-KN	15W	120-277V	4000K	1,603 lm	111 lm/W	N/A
FLM-15W-40K-LV-YK	15W	120-277V	4000K	1,603 lm	111 lm/W	N/A
FLM-30W-3CCT-LV	21W / 24W / 27W / 30W	120-277V	3000K / 4000K / 5000K	4,141 lm	148 lm/W	Premium
FLM-50W-3CCT-LV	35W / 40W / 45W / 50W	120-277V	3000K / 4000K / 5000K	7,148 lm	149 lm/W	Premium
FLM-70W-3CCT-UD	49W / 56W / 63W / 70W	120-347V	3000K / 4000K / 5000K	9,526 lm	129 lm/W	Premium
FLM-90W-3CCT-UD	63W / 72W / 81W / 90W	120-347V	3000K / 4000K / 5000K	11,320 lm	125 lm/W	Premium

*Shown at highest wattage and lowest CCT

FLM-KNS	Knuckle Mount for FLM 30W and 50W fixtures	
FLM-KNL	Knuckle Mount for FLM 70W and 90W fixtures	
FLM-SF	Slip Fitter for FLM 70W and 90W fixtures	
FLM-STK	Stake for FLM series Flood / Area lights	NOTE: Must be used with Knuckle Mount (Sold Separately)
FLM-30W-BLU	Blue Lens for FLM 30W fixtures	
FLM-30W-GRN	Green Lens for FLM 30W fixtures	
FLM-30W-RED	Red Lens for FLM 30W fixtures	
FLM-50W-BLU	Blue Lens for FLM 50W fixtures	
FLM-50W-GRN	Green Lens for FLM 50W fixtures	
FLM-50W-RED	Red Lens for FLM 50W fixtures	



FLM-15W-40K-YK



FLM-30W-3CCT-LV



FLM-15W-40K-KN



FLM-50W-3CCT-LV



FLM-70W-3CCT-UD
FLM-90W-3CCT-UD



FLM-STK

Pictured: FLM-15W with Stake